NEURAL NETWORK FOR SONOGRAM GAP FILLING

Henrik Klebæk, Jørgen Arendt Jensen, and Lars Kai Hansen

Electronics Institute, Build. 349, Technical University of Denmark, DK-2800 Lyngby, Denmark

Abstract

In duplex imaging both an anatomical B-mode image and a sonogram are acquired, and the time for data acquisition is divided between the two images. This gives problems when rapid B-mode image display is needed, since there is not time for measuring the velocity data. Gaps then appear in the sonogram and in the audio signal, rendering the audio signal useless, thus making diagnosis difficult.

The current goal for ultrasound scanners is to maintain a high refresh rate for the B-mode image and at the same time attain a high maximum velocity in the sonogram display. This precludes the intermixing of the B-mode and sonogram pulses, and time must be shared between the two. Gaps will appear frequently in the sonogram since, *e.g.*, half the time is spent on B-mode acquisition. The information in the gaps can be filled from the available information through interpolation. One possibility is to use a neural network for predicting mean frequency of the velocity signal and its variance. The neural network then predicts the evolution of the mean and variance in the gaps, and the sonogram and audio signal are reconstructed from these.

The technique is applied on *in-vivo* data from the carotid artery. The neural network is trained on part of the data and the network is pruned by the optimal brain damage procedure in order to reduce the number of parameters in the network, and thereby reduce the risk of overfitting. The neural predictor is compared to using a linear filter for the mean and variance time series, and is shown to yield better results, *i.e.*, the variances of the predictions are lower. The ability of the neural predictor to reconstruct both the sonogram and the audio signal, when only 50% of the time is used for velocity data acquisition, is demonstrated for the *in-vivo* data.

1 Introduction

Pulsed ultrasound systems are widely used for probing the human circulatory system for finding the distribution of blood velocities in arteries, veins, and heart chambers. The velocity distribution is found by emitting a series of pulses into the human body, and acquiring a single sample at a fixed depth for each pulse emitted. The velocity of the blood scatterers generates a signal with a frequency proportional to the velocity v_z of the blood along the ultrasound beam direction [1]. The frequency is given by

$$f_p = \frac{2v_z}{c} f_0 \tag{1}$$

where c is the speed of sound and f_0 the center frequency of the emitted pulse. A spread in velocities gives a corresponding spread in frequencies and the power density spectrum of the received, stochastic signal thus reveals the velocity distribution. A typical display is to show the power density spectrum as a function of time, where the x-axis is time, the y-axis is frequency, and the gray scale value corresponds to power density. Such a display is called a sonogram or spectrogram. A Fourier transform is done on small segments of data to calculate the power density. Often 64 to 128 pulse-echo lines are used, and this necessitates, *e.g.* 12 to 25 ms of data at a pulse repetition frequency of 5 kHz.

To assist in placing the interrogation volume or range gate, a dynamic B-mode image is shown alongside the sonogram display. Time for data acquisition is then split between the two images. The highest velocity that can be detected is dependent on the pulse repetition frequency f_{prf} as

$$v_{max} = \frac{c}{2} \frac{f_{prf}}{2f_0} \tag{2}$$

The interspacing of the B-mode pulses with the sonogram pulses then conflicts with the demand of a high v_{max}, since f_{prf} is reduced by the fraction of time used on the B-mode image. One solution is to alternate between acquiring a number of B-mode lines and sonogram lines, as shown in Fig. 1. Gaps then appear in the sonogram, when the B-mode image is acquired, and this severely distorts the audio signal. This is disruptive to the physician, and the gaps should be filled.

A gap filling approach has been suggested by Kristoffersen and Angelsen (1988). They used a FIR filter determined by the power density spectrum of the signal